Terminal for two-tiered installation for surface mounting [HRP series] (10pcs/pack)

- By fitting this product to the master board side (surface mounting) and fitting a socket pin (with a hole) on the slave board side, this terminal allows two-tiered installation and inserting / pulling out.
- This can be used by direct soldering without using a socket.
- Pitch: 2.54 mm, 20P connected
- Operating temperature range: -40 to +125°C
- Material

Pin part: Brass

Resin part: PPS black (UL94V-0)

Finish


Part number	Finish	
HRP-20P-G	Gold plating over nickel base	
HRP-20P-S	Tin plating over nickel base	


Rated current

When a socket is used: 1A When directly soldered: 2A

- Insulation resistance:500M Ω or over
- Withstand voltage: 1000V AC, DC per minute


Recommended fitting land





HR-20P and ME-3-1

PC board



riditiditiditidi

Example of usage

Example of usage

an adhesive to several places. Reference dimensions

Instructions for mounting

Master board side	Slave board side	Height between the boards: H (mm)	
HRP-20P-G	ME-3-1	4.7	
HRP-20P-S	MF-3-1	4.7	
"	PD-7	2.6	
"	PC-10	2.7	
"	PC-11	2.7	
"	Direct soldering	2.2	

In the case that a warpage occurs on the resin part during

reflow because many pins are connected for use, apply

How to order

HRP-10P-G G: Gold plating over nickel base S: Tin plating over nickel base Please fill in the desired number of poles.

(Maximum number: 20P)

HRP-20P and PD-7

0.40

P=2.54


0.64

Hole: $\phi 2 - \phi 1.0$

3.0

Terminal for two-tiered installation for surface mounting (with placement pin) [HRRP series] (10pcs/pack)

- This terminal has a placement pin that allows easy positioning of the terminal for two-tiered installation for surface mounting described above.
- Placement pin material: Phosphor bronze 0.64□
- Fitting hole diameter: φ 1.1
- We will deliver it with the desired number of poles.



Recommended fitting land 2.0 or ove (The number of poles does not include the placement pin.) There are 10 valid pins and placement pins on the both sides. (Maximum number: 18P)

Instructions for mounting

In the case that a warpage occurs on the resin part during reflow because many pins are connected for use, apply an adhesive to several places.