

For check

Check terminal for logic [ST series] (1000pcs/pack)

- Best solution for a logic circuit.
- This terminal can be inserted in a hole of ϕ 0.5、 ϕ 0.6、 ϕ 0.8、 ϕ 1.0 and ϕ 1.2
- This terminal can be fit to a through hole land for upper and lower electrical connection.
- Material: Brass
- Finish: Gold plating over nickel base





Table of dimensions

Part number	D ₁	D ₂	D ₃	D ₄	D ₅	H	Printed board fitting hole diameter
ST-1-1	2.0 ϕ	1.8 ϕ	1.2 ϕ	0.8 ϕ	0.65 ϕ	3.0	0.8 ϕ
ST-1-2	2.0	1.8	1.2	0.8	0.65	6.0	0.8
ST-1-3	2.0	1.8	1.2	0.8	0.65	10.0	0.8
ST-2-1	2.5	2.2	1.4	1.0	0.8	3.5	1.0
ST-2-2	2.5	2.2	1.4	1.0	0.8	6.5	1.0
ST-2-3	2.5	2.2	1.4	1.0	0.8	10.5	1.0
ST-3-1	2.5	2.2	1.4	1.2	1.0	3.5	1.2
ST-3-2	2.5	2.2	1.4	1.2	1.0	6.5	1.2
ST-3-3	2.5	2.2	1.4	1.2	1.0	10.5	1.2
ST-4-1	1.5	1.5	1.0	0.8	0.65	3.0	0.8
ST-4-2	1.5	1.5	1.0	0.8	0.65	5.0	0.8
ST-5-1	1.2	1.2	0.8	0.6	0.5	3.0	0.6
ST-5-2	1.2	1.2	0.8	0.6	0.5	5.0	0.6
ST-6-1	1.0	1.0	0.7	0.5	0.4	3.0	0.5
ST-6-2	1.0	1.0	0.7	0.5	0.4	5.0	0.5

Check terminal for logic [SB series] (1000pcs/pack)

For printed board with a thickness of 3.2t

- This is a check terminal to be used for a PC board with a thickness of 3.2t.
- Material: Brass
- Finish: Gold plating over nickel base





Table of dimensions

Part number	D ₁	D ₂	D ₃	D ₄	D ₅	H	Printed board fitting hole diameter
SB-1-1	1.5 ϕ	1.2 ϕ	0.8 ϕ	0.8 ϕ	0.65 ϕ	3.0	0.8 ϕ
SB-1-2	1.5	1.2	0.8	0.8	0.65	5.0	0.8
SB-2-1	2.0	1.5	1.0	1.0	0.8	3.5	1.0
SB-2-2	2.0	1.5	1.0	1.0	0.8	6.5	1.0